



Models- 9225 – 9235
Commercial Vacuums

Page 2	Product Information
Page 3	Product Dimensions
Page 4	Specifications
Page 5	Important Safety Instructions
Page 5-8	Installation
Page 9	Programming
Page 10	Operating
Page 10	Maintenance
Page 11	Troubleshooting
Page 12-17	Parts List
Page 18-21	Wiring Diagram



PRODUCT INFORMATION

Please take a moment to fill out the information below in order to aid us with any future sales or service inquiries. Model number and serial number information can be found on the serial tag located inside the control box and/or on the lower exterior of the can. Key number can be found on the tag that comes attached to the keys. There may be more than one key number depending on unit.

Please keep this information with your records.

MODEL#:_____

SERIAL#:_____



KEY NUMBER(S):_____

DATE PURCHASED:_____

DISTRIBUTOR:_____

**J.E. Adams Industries
1025 63rd Ave. S.W.
Cedar Rapids, IA 52404
1-800-553-8861
www.jeadams.com**

PRODUCT DIMENSIONS



Specifications

Unit specifications: (9225, 9225-2, 9235, 9235LD)

Voltage: 120vac, 60hz
Amperage: (1) 20 amp service is required for this unit.
Weight: 110-135 lbs with pallet attached.

2 Motor 120V Vacuum Units

Vac specifications:

Motors: (2) 120vac vacuum motors.
Fuses: (2) 10 amp inline fuses.

Unit specifications: (9225-3, 9235-3, 9235-3LD, 9235-3DH, 9235-3DH-WALL)

Voltage: 120vac, 60hz
Amperage: (1) 30 amp service is required for this unit.
Weight: 140 lbs with pallet attached.

3 Motor 120V Vacuum Units

Vac specifications: (9225-3, 9235-3, 9235-3LD, 9235-3DH, 9235-3DH-WALL)

Motors: (3) 120vac vacuum motors.
Fuses: (3) 10 amp inline fuses.

Unit specifications: (9225-220V, 9235-220V, *9235-3-220V, *9235-3DH-220V)

Voltage: 220v, 50hz
Amperage: (1) 15 amp service is required for 2 motor units, *(1) 20 amp service is required for 3 motor units.
Weight: 125-140 lbs with pallet attached.

2 & 3 Motor 220V Vacuum Units

Vac specifications:

Motors: (2) or (3) 220vac vacuum motors depending on model.
Fuses: (2) or (3) 8 amp inline fuses, depending on model.

Duty cycle time 4 minutes on, 4 minutes off.

NOTE: "UNIT INTENDED FOR COMMECIAL USE ONLY"


IMPORTANT SAFETY INSTRUCTIONS

When using an electrical appliance, basic precautions should always be followed, including the following:

READ ALL INSTRUCTIONS BEFORE USING (THIS APPLIANCE)


WARNING – To reduce the risk of fire, electric shock, or injury:

- Do not use on wet surfaces.
- Use only as described in manual. Use only manufactures recommended attachments.
- Do not allow to be used as a toy. Close attention is necessary when used by or near children.
- Do not put any object into openings. Do not use with any opening blocked; keep free of dust, lint, hair and anything that may reduce air flow.
- Keep hair, loose clothing, fingers, and all parts of body away from openings and moving parts.
- Do not use to pick up flammable or combustible liquids, such as gasoline, or use in areas where they may be present.
- Do not pick up anything that is burning or smoking, such as cigarettes, matches, or hot ashes.
- Do not use without dust bag and/or filters in place.





SAVE THESE INSTRUCTIONS

- **Installation Instructions:**
- Determine location to mount unit (**“DANGER” “THIS EQUIPMENT INCORPORATES PARTS SUCH AS SWITCHES, MOTORS, OR THE LIKE THAT TEND TO PRODUCE ARCS OR SPARKS THAT CAN CAUSE AN EXPLOSION. WHEN LOCATED IN GASOLINE-DISPENSING AND SERVICE STATIONS INSTALL AND USE AT LEAST 20 FEET (6 M) HORIZONTALLY FROM THE EXTERIOR ENCLOSURE OF ANY DISPENSING PUMP AND AT LEAST 18 INCHES (450 MM) ABOVE A DRIVEWAY OR GROUND LEVEL.”**)
- Run electrical service to that location (*NOTE UNIT HAS WIRE PROVIDED UNDERNEATH TO CONNECT INCOMING POWER SUPPLY*)
- **Grounding Instructions:** This appliance must be connected to a grounded metal, permanent wiring system; or an equipment-grounding conductor must be run with the circuit conductors and connected to the equipment-grounding terminal or lead on the appliance.
- **Circuit must be protected by GFCI device.**
- All local and national electric codes must be followed for installation and use.
- Licensed electricians are recommended for installation.



Once unit has been installed use 5871B8 cap plugs (supplied with unit) to seal holes in canister bottom located in lower cleanout door (see illustration on subsequent page). Extra cap plugs are included with the unit in case plug becomes damaged during shipping removal. After cap plugs are installed, then connect unit to power (see below illustration). NOTE: when mounting unit, don't forget to allow clearance for clean-out door to swing open.

Floor standing model






Remove cover and tie into factory electrical here. Note: end user must provide on/off switch.

Bring incoming power through this conduit hole.

Once unit has been installed use 5871B8 cap plugs (supplied with unit) to seal holes in canister bottom located in lower cleanout door (see illustration on next page). Extra cap plugs are included with the unit in case plug becomes damaged during shipping removal. After cap plugs are installed, then connect unit to power (see below illustration). NOTE: when mounting unit, don't forget to allow clearance for clean-out door to swing open.


Drill 4 holes for support brackets, size according to hardware – use 5/8 diameter minimum for hardware.




Installation hardware needs to be selected by the end user as installation surfaces vary from concrete, to block, to wood walls. Height to install to is also up to the end user. Use at least two people to lift during installation.

Wall mount model

To attach hose, thread
into metal hole
counter clockwise.



Edge of
hose will
need to start
here.




To insert 5871B8 cap plugs into bottom holes, pinch
cap plug into place using index finger and thumb.
With edges of plug resting against edges of hole,
firmly push down on plug with end of hammer or other
blunt object until plug snaps into place.

Programming:

JE Adams commercial vacuum models typically come with an "on/off" toggle switch, but are also available with the optional push button kit which incorporates the use of a timer. The below timer pictured is the standard SSAC model that allows the end user to select the "coins to start" and the "total time" by settings series of dip switches. The number of "coins to start" dip switch is how many quarters are needed to make the machine come on. In the below example, the "one coin" dip is selected which makes the unit come on with one coin. The "total time" will then need to be set, but a good rule of thumb would be 4 minutes which requires dip switches 3.2 and .8 to be set to on. This scenario means 1 quarter will provide 4 minutes of vacuum time. The total time can always be changed by adding or subtracting time. If the operator would later decide to increase the cost of the unit to "2" quarters, the 2 dip switch would need to be in the on position (all others off) and the time dip switches would still be 3.2 and .8 dips selected for 4 minutes. Timer is non accumulating so "coins to start" setting is just to make the machine come on time and "time" is total time regardless of coins to start.

NOTE: In the case of a free vend machine that incorporates the use of a push button, COINS TO START is set at 1.



Time in minutes; dip switch settings:

0.2 = 12 seconds

0.4 = 24 seconds

0.8 = 48 seconds

1.6 = 96 seconds

3.2 = 192 seconds

6.4 = 384 seconds

Total time
(non accumulating)

Coins To Start

Operating Instructions:

- Turn toggle switch to on position when machine needs to run, and off position when finished.
- In the case of a push button kit, press push button to activate machine. It will automatically shut off.
- Remove vacuum hose from hanger and vacuum subject accordingly. Do not vacuum wet objects or fine dust (ex – drywall dust).
- Return vacuum hose to hanger when finished.
- In the case of a dual hose model, hose claw must be returned to hanger and set against rubber pad to eliminate leaks in vacuum system. This will allow the opposite hose to have more suction while in use.

Maintenance:

- **All servicing of machine should be conducted by an authorized service representative!**
- Filter bags should be accessed and shaken down weekly. It is recommended to keep a new set of bags on hand so that once every few months the bags can be replaced and then laundered.
- To maintain performance, empty dirt bin from the canister on a regular basis.
- Periodically inspect wires and connections for wear or fatigue.
- Check vac hose for cracks on a weekly basis.
- Clean canister with a stainless steel cleaner as needed. Decals can be cleaned with mild soap and water.
- Check motor brushes approx. every 3 months for excessive wear. Motor brushes should be changed if they are shorter than 3/8". ***Please disconnect power before doing this.***





DISCONNECT POWER BEFORE SERVICING OR TROUBLESHOOTING!





Troubleshooting: **!DISCONNECT POWER BEFORE SERVICING OR TROUBLESHOOTING!**

Problem	Possible cause	Solution
Unit is not powered.	Breaker inside fuse panel is not in the on position.	Turn breaker on.
	No power to machine.	Check incoming power line voltage.
	Loose connection.	Check incoming power connection.
Machine is behaving erratically.	Is the incoming power at 120V?	Check voltage and monitor while machine runs. Low voltage can cause erratic behavior.
	Are any of the machines wires worn through or connections not making contact?	Inspect wiring and connections. Look for sharp bends in wires and places where wire is against the metal chassis.
Unit keeps tripping breaker.	Inadequate wire size ran to machine.	Call electrician and install proper wire size for electrical service versus length or run.
	Wrong size breaker.	Install correct breaker (only if wire size is adequate to handle breaker).
Fuses for vac motors keep blowing.	Inadequate wire size ran to machine.	Call electrician and install proper wire size for electrical service versus length or run.
	Motor brushes may be bad or too short.	Replace motor brushes.
Lack of vacuum suction.	Vac hose clogged?	Clean debris from vac hose.
	Filter bags need cleaned or dirt chamber needs emptied?	Shake or clean filter bags or replace and empty lower dirt chamber.
	Vac hose is split?	Replace/repair vac hose.
	Cleanout door gaskets torn or worn?	Replace gaskets.
	Vac motor gaskets are worn or motor is not tight against.	Inspect/replace gaskets and assure motor is tight against them.
	Dual vac hose unit, both hoses are being used.	When both hoses are being used, suction will be lower. Double check all 3 motors are working however.
	Lower chamber cap plugs/mounting hole covers have popped out?	Open lower chamber and inspect plugs, order new if needed.
	Cleanout door gaskets torn or worn?	Replace gaskets.
	One of the vac motors is not working?	Check line motor fuse and replace. Replace motor if necessary.





PART NO.		9225											
BILL OF MATERIALS				BILL OF MATERIALS									
ITEM	PART NUMBER	DESCRIPTION	QTY	ITEM	PART NUMBER	DESCRIPTION	QTY						
31	8159	DOOR GASKET	2	1	1000	BIRD SEED, 10LBS	1						
32	8183	DECAL, WARNING	2	2	2036	HOSE, 2" X 15' BLACK VACUUM	1						
33	8423-2	DECAL, DOME	1	3	2058	CLAW/CUFF ASSEMBLY, 2"	1						
34	8427-1	DECAL, CANISTER	1	4	5600D4	3/8-16 X 1.5 HHCS	4						
35	8429-1	DECAL, HANG HOSE	1	5	5603D1	10 Std NC Nylock Nut	1						
36	8437D001	DECAL, ETL LISTED	1	6	5603D11	1/2 Std NF Nylock Nut	1						
37	8505-1	COVER, CONTROL PLATE	1	7	5606D22	WASHER, 3/8 FENDER	8						
38	8605	PALLET, VAC, 26" X 30.5"	1	8	5606D7	FLAT WASHER, .160 ID X .500 OD	1						
39	8615-5W	CLEANOUT DOOR WELDMENT	2	9	5619D1	SCR, HEX SOC BUT, HD CPCW, 1	4						
40	8631	11 X 55 PAD FOR VAC	1	10	5627D2	6-32 x .63 PD, PH, MS	1						
41	8673-10	2 MTR COMMERCIAL WIRE HARNESS	1	11	5636D1	#10-24 PHIL. PAN HEAD SCREW	2						
42	9226W	CANISTER WELDMENT, 2D, COMMERCIAL	1	12	5639D4	RUBBER GROMMET	1						
43	B5722-002	NUT, 3/8-16 UNC HEX LOCK NUT	4	13	5647D2	1/8" SS POP RIVET	16						
				14	5647D8	3/16" SS POP RIVET	14						
				15	5871B9	PLASTIC VAC LID PLUG	4						
				16	5871b8	PLUG, VAC BOTTOM 2-1/2"	8						
				17	5901D1	YELLOW WIRE NUT	2						
				18	5901D4	ORANGE WIRE NUT	2						
				19	6082	BAG, 9 X 12	1						
				20	8047	BAG, 60 X 72	1						
				21	8051G	BRACKET, MOTOR MOUNT	1						
				22	8055EM	MOTOR, ELECTRO 120V	2						
				23	8057	MOTOR GASKET	2						
				24	8076	FILTER BAG	4						
				25	8081	CABLE TIE MOUNT	2						
				26	8084	CABLE TIE	3						
				27	8101	20" STAINLESS STEEL DOME	1						
				28	8108	#10 x 1/2 TAP SCREW	4						
				29	8153-1	LATCH, CLEANOUT DOOR	4						
				30	8157	NUT, #6-32 KEPP NUT STAINLESS	1						
H	7890	REMOVED 8424-1 AND ADDED 8427-1	11-21-16	CK	TITLE VAC, 2DR, COMMERCIAL								
G	7727	REMOVED 5920, 8055LEAD-EM, 8221WH2, 8828	4-5-16	CK									
F	7151	REMOVED 8630B36	8-29-13	CK	UNSPECIFIED TOLERANCES	MATERIAL							
E	6472	REVISED AND REDRAWN TO INVENTOR FROM AUTOCAD	4-26-11	CK	1 PL ±.030	SCALE							
REV	NO.	DESCRIPTION	DATE	BY	2 PL ±.010	DRAWN BY							
					3 PL ±.003	CHAD K.							
					ANGLE ±1.0°	DATE							
THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES					4/26/2011		PART NO.	9225	REV.	H			

PART
NO.


9225



SECTION A-A



DETAIL C





DETAIL D

REV	NO.	DESCRIPTION	DATE	BY
-----	-----	-------------	------	----



THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE
USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES

TITLE				VAC, 2DR, COMMERCIAL		
UNSPECIFIED TOLERANCES	MATERIAL		 CEDAR RAPIDS, IOWA			
	SCALE					
	1 PL ±.030		DRAWN BY			
	2 PL ±.010		CHAD K.			
3 PL ±.003		DATE		PART NO.		REV.
ANGLE ±1.0°		4/26/2011		9225		H





PART NO. 9235-3LD											
BILL OF MATERIALS				BILL OF MATERIALS							
ITEM	PART NUMBER	DESCRIPTION	QTY	ITEM	PART NUMBER	DESCRIPTION	QTY				
32	8543K-3	3 MOTOR LIGHT KIT	1	1	1000	BIRD SEED, 10LBS	1				
33	8605	PALLET, VAC, 26" X 30.5"	1	2	2036	HOSE, 2" X 15' BLACK VACUUM	1				
34	8615-5W	CLEANOUT DOOR WELDMENT	2	3	2058	CLAW/CUFF ASSEMBLY, 2"	1				
35	8631	11 X 55 PAD FOR VAC	1	4	5600D4	3/8-16 X 1.5 HHCS	4				
36	8673-10-3	3 MTR COMMERCIAL WIRE HARNESS	1	5	5601D13	SCR,1/4-20x1/2 PPHSqConeStepZP	4				
37	8732	NAMEPLATE, PRODUCT SPEC'S	1	6	5603D1	10 Std NC Nylock Nut	1				
38	8754	WARNING DECAL	1	7	5603D11	1/2 Std NF Nylock Nut	1				
39	8925	FLOURESCENT BULB	3	8	5606D22	WASHER, 3/8 FENDER	8				
40	9236-3W	CANISTER WELDMENT, 2D, 3 MTR COMMERCIAL	1	9	5606D7	FLAT WASHER, .160 ID X .500 OD	1				
41	B5722-002	NUT, 3/8-16 UNC HEX LOCK NUT	4	10	5627D2	6-32 x .63 PD, PH, MS	1				
				11	5636D1	#10-24 PHIL. PAN HEAD SCREW	2				
				12	5647D2	1/8" SS POP RIVET	16				
				13	5647D8	3/16" SS POP RIVET	14				
				14	5871b8	PLUG, VAC BOTTOM 2-1/2"	8				
				15	6082	BAG, 9 X 12	1				
				16	8047	BAG, 60 X 72	1				
				17	8055EM	MOTOR, ELECTRO 120V	3				
				18	8057	MOTOR GASKET	3				
				19	8076	FILTER BAG	4				
				20	8081	CABLE TIE MOUNT	2				
				21	8084	CABLE TIE	3				
				22	8108	#10 x 1/2 TAP SCREW	6				
				23	8153-1	LATCH, CLEANOUT DOOR	4				
				24	8157	NUT, #6-32 KEPP NUT STAINLESS	1				
				25	8159	DOOR GASKET	2				
				26	8183	DECAL, WARNING	2				
				27	8306	24" PLASTIC DOME	1				
				28	8427-1	DECAL, CANISTER	1				
				29	8429-1	DECAL, HANG HOSE	1				
				30	8437D001	DECAL, ETL LISTED	1				
				31	8505-1	COVER, CONTROL PLATE	1				
C	7890	REMOVED 8424-1 AND ADDED 8427-1	11-22-16	CK	TITLE VAC, 2DR, 3 MOTOR COMMERCIAL, LD UNSPECIFIED TOLERANCES 1 PL ±.030 2 PL ±.010 3 PL ±.003 ANGLE ±1.0°						
B	7727	REMOVED 5920, 8221WH3, 8828	4-5-16	CK							
A	6486	REVISED AND DRAWN TO INVENTOR; NO PREVIOUS DRAWING	4-29-11	CK							
REV	NO.	DESCRIPTION	DATE	BY							
THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES					MATERIAL SCALE DRAWN BY CHAD K. DATE 4/29/2011			PART NO. 9235-3LD REV. C			
								CEDAR RAPIDS, IOWA			

PART
NO.

9235-3LD



SECTION A-A



DETAIL B

DETAIL C

TITLE
VAC, 2DR, 3 MOTOR COMMERCIAL, LD

UNSPECIFIED
TOLERANCES

1 PL ±.030
2 PL ±.010
3 PL ±.003
ANGLE ±1.0°

MATERIAL

SCALE

DRAWN
BY CHAD K.

DATE 4/29/2011

CEDAR RAPIDS, IOWA



PART
NO.

9235-3LD


REV.
C

REV	NO.	DESCRIPTION	DATE	BY
THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES				



NOTES:

1. PACKAGE CLAW HANGERS IN SH111
TO PROTECT FROM SHIPPING DAMAGE.




THIS MODEL IS A SPECIAL
"DUAL HOSE" UNIT BASED
ON JE ADAMS MODEL 9235-3.
NOTE: HOSES HAVE LIMITED
SHUTOFFS BUT MOST AIR FLOW
IS OBSTRUCTED WHILE HOSES
HANG IN HOLDERS.

BILL OF MATERIALS				BILL OF MATERIALS			
ITEM	PART NUMBER	DESCRIPTION	QTY	ITEM	PART NUMBER	DESCRIPTION	QTY
30	8597	WASHER, 5/16 SAE FLAT ZP	3	1	9236-3W-DH	3 MOTOR VAC CANISTER W/C	1
31	8598	WASHER, 5/16 LOCK ZP	3	2	8057	MOTOR GASKET	3
32	8732	NAME PLATE, PRODUCT SPEC	1	3	8055EM	MOTOR, ELECTRO 120V	3
33	8437D001	DECAL - ETL LISTED ANSI/UL	1	4	8051-3M	3 MOTOR BRACKET	1
34	5871B8	PLUG, RECESSED	8	5	5603D11	1/2 Std NF Nylock Nut	1
35	6082	BAG 9 X 12	1	6	8076	FILTER BAG	4
36	2058-13A-9	CLAW HANGER ASSEMBLY, VAC MNT	2	7	8108	#10 x 1/2 TAP SCREW	6
37	SH111	BOX, 6X6X5 SHIPPING	1	8	5611D2	NUT, 10-24 UNC KEPP- ZINC	1
40	8427-1	DECAL, VACUUM	2	9	5639D1	RUBBER GROMMET	1
41	8423-2	DECAL, VACUUM DOME	1	10	5627D2	6-32 x .63 PD, PH, MS	2
42	8673-10-3	WIRING ASSY	1	11	8305	ASSEMBLED SS DOME	1
46	5901D2	WIRE NUT, RED	2	12	8505-1	COVER, CONTROL PLATE	1
47		PACKAGING		15	2036	HOSE, 2" X 15' BLACK VACUUM	2
48	5600D4	BOLT HHEAD 3/8-16 X 1-1/2	4	16	2058	CLAW/CUFF ASSEMBLY, 2"	2
49	5606D22	FENDER WASHER, 3/8	8	17	5636D1	#10-24 PHIL. PAN HEAD SCREW	1
50	B5722-002	NUT, HEX LOCKNUT	4	18	8159	DOOR GASKET	2
51	8939	PALLET	1	19	8615-5W	CLEANOUT DOOR WELDMENT	2
52	8631	11 X 55 PAD	1	20	8153-1	LATCH, CLEANOUT DOOR	4
				21	8081	CABLE TIE MOUNT	1
				22	8084	CABLE TIE NYLON	3
				23	8100N002	INS TAG, YELLOW REMOVE	1
				24	5647D2	RIVET - 1/8 SS POP	16
				26	8183	DECAL, WARNING ENGLISH/FRENCH	1
				27	8754	DECAL, DANGER ENG/FR/SPAN	1
				28	8595	HHCS 5/16 X 1-1/2 ZP	3
				29	8596	NUT, 5/16-18 HEX ZP	3

F	8575	REMOVED 2058-13W, 2058-4, 2058-3, 5601D4, 5603D2, ADD 2058-13A-9, SH111	3/17/20	MWS
E	7727	REMOVED 8828, 5920, 8055LEAD-EM, B5996-010, B5997-001	4-5-16	CK
D	7374	ADD ITEM 53, NOTE 1, ITEM 36 WAS 9280F22.	12/22/14	MWS
C	5541	CHANGE TO LARGER PALLET 8939, WAS 8605	020910	JF
B	5293	ADJUST BILL FOR NEW WIRING HARNESS WITH SWITCH	100709	JF
REV	NO.	DESCRIPTION	DATE	BY

TITLE		COMMERCIAL VAC - 3 MOTOR, 2 DOOR	
UNSPECIFIED TOLERANCES	MATERIAL	CEDAR RAPIDS, IOWA	
1 PL ±.030	DRAWN BY JOHN F		
2 PL ±.020	DATE 12/22/2008		
3 PL ±.003	SCALE		
ANGLE ±1°	SHEET 1 / 2	PART NO. 9235-3DH	REV. F


THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES



9235-3DH
SCALE .1

				TITLE				COMMERCIAL VAC - 3 MOTOR, 2 DOOR			
				UNSPECIFIED TOLERANCES				MATERIAL		CEDAR RAPIDS, IOWA	
				1 PL ± .030				DRAWN BY		JOHN F	
				2 PL ± .020				DATE		12/22/2008	
				3 PL ± .003				SCALE		SHEET	
				ANGLE ± 1°						2 / 2	
								PART NO		REV.	
								9235-3DH		F	
THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES											


ITEM NO.	PART NO.	DESCRIPTION	QTY.
-------------	----------	-------------	------

**!! IMPORTANT !!**


TERMINAL STRIP IS ON BACK SIDE OF TIMER
PLATE IN LOCK BOX
FIELD WIRING MUST COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES

***30AMP SERVICE IS
REQUIRED***

TITLE
3 MOTOR COMMERCIAL, ON-OFF TOGGLE

UNSPECIFIED TOLERANCES	SCALE	 <p>CEDAR RAPIDS, IOWA</p>	REV.
FRACT. $\pm 1/32$	DRAWN BY CK		
2 PL $\pm .020$	DATE 7-27-11		
3 PL $\pm .010$	REL. FOR PROD. -	PART NO. 3 MOTOR COMMERCIAL	
ANGLE $\pm 1.0^\circ$			


ITEM NO.	PART NO.	DESCRIPTION	QTY.
-------------	----------	-------------	------






**!! IMPORTANT !!**

TERMINAL STRIP IS ON BACK SIDE OF TIMER
PLATE IN LOCK BOX
FIELD WIRING MUST COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES

***20AMP SERVICE IS
REQUIRED***

220V with toggle




TITLE		3 MOTOR COMMERCIAL, TOGGLE, 220VAC	
UNSPECIFIED TOLERANCES FRACT. $\pm 1/32$ 2 PL $\pm .020$ 3 PL $\pm .010$ ANGLE $\pm 1.0^\circ$	SCALE		
	DRAWN BY	JF	
	DATE	7/25/11	
	REL. FOR PROD.	-	
			
		CEDAR RAPIDS, IOWA	
PART NO. 3		MOTOR COMMERCIAL	
		REV.	


COIN ACCEPTORS SSAC

OPTIONAL TIMERS

COIN ACCEPTORS IDX & INFITEC

IMPORTANT INFORMATION

!! IMPORTANT !!
TERMINAL STRIP IS ON BACK SIDE OF
TIMER PLATE IN LOCK BOX. FIELD
WIRING MUST COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES
***20AMP SERVICE IS REQUIRED
FOR 2 MOTOR UNIT***

!! IMPORTANT !!
TERMINAL STRIP IS ON BACK SIDE OF
TIMER PLATE IN LOCK BOX. FIELD
WIRING MUST COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES
***30AMP SERVICE IS REQUIRED
FOR 3 MOTOR UNIT***

LIGHTED DOME

OPTIONAL COUNTERS


C	8638	MODIFY NOTES FOR 1-COIN MECH	08/20/20	JRF
B	8142	CHANGED WIRE CONFIGURATION OF SENSORTRON	12-20-17	CK
A	7689	SPLIT COIN ACCEPTOR FOR USE WITH SSAC OR IDX & INFITEC	2-23-16	CK
REV	NO.	DESCRIPTION	DATE	BY

THIS DOCUMENT SHALL NOT BE
REPRODUCED NOR SHALL THE
INFORMATION THEREIN BE USED
BY OR DISCLOSED TO OTHERS
EXCEPT AS AUTHORIZED BY
J.E. ADAMS INDUSTRIES



PART NO.
VACUUM 120V




UNSPECIFIED
TOLERANCES
1 PL ±.030
2 PL ±.010
3 PL ±.003
ANGLE 1:10

TITLE	VACUUM 120V			
DESIGNED BY	CHAD K.	DATE	12/16/15	SCALE
NATURAL	-	REL. FOR PROJ.	NONE	REV. LEVEL
PART NO.	VACUUM 120V			
				C


VACUUM STANDARD



OPTIONAL TIMERS



COIN ACCEPTORS IDX & INFITEC



IMPORTANT INFORMATION



!! IMPORTANT !!
TERMINAL STRIP IS ON BACK SIDE OF
TIMER PLATE IN LOCK BOX. FIELD
WIRING MUST COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES
***15AMP SERVICE IS REQUIRED
FOR 2 MOTOR UNIT***


!! IMPORTANT !!
TERMINAL STRIP IS ON BACK SIDE OF
TIMER PLATE IN LOCK BOX. FIELD
WIRING **MUST** COMPLY WITH LOCAL AND
NATIONAL ELECTRICAL CODES
***20AMP SERVICE IS REQUIRED
FOR 3 MOTOR UNIT***

LIGHTED DOME



OPTIONAL COUNTERS



				THIS DOCUMENT SHALL NOT BE REPRODUCED NOR SHALL THE INFORMATION THEREIN BE USED BY OR DISCLOSED TO OTHERS EXCEPT AS AUTHORIZED BY J.E. ADAMS INDUSTRIES.		 CEDAR RAPIDS, IOWA		UNSPECIFIED TOLERANCES: 1 PL ±.030 2 PL ±.010 3 PL ±.003 ANGLE ±1.0		TITLE: VACUUM 220V DRAWN BY: CHAD K. DATE: 3-7-16 SCALE: NONE REL. FOR FABR.: MATERIAL: - PART NO.: VACUUM 220V REV. LEVEL: A			
A	8638	MODIFY NOTES FOR I-COIN MECH		08/20/20	JRF								
REV	NO.	DESCRIPTION		DATE	BY								